


## Data sheet | Item number: 855-4105/300-101

Split-core current transformer; Primary rated current 300 A; Secondary rated current: 5 A; Rated power: 1 VA; Accuracy class: 1



[www.wago.com/855-4105/300-101](http://www.wago.com/855-4105/300-101)



 Picture differs from the item.

RoHS  
Compliant

BOMcheck.net



### Item description

#### Short description:

WAGO's compact split-core current transformers are ideal for retrofitting existing systems. They are perfect for applications in which the current path must not be disrupted.

The transformer's accuracy permits extremely precise current measurements. The split-core current transformers are capable of supplying the specified rated power at

Subject to changes. Please also observe the further product documentation!

WAGO Kontakttechnik GmbH & Co. KG  
Hansastr. 27  
32423 Minden  
Phone: +49571 887-0 | Fax: +49571 887-169  
Email: [info.de@wago.com](mailto:info.de@wago.com) | Web: [www.wago.com](http://www.wago.com)

Do you have any questions about our products?  
We are always happy to take your call at +49 (571) 887-44222.

the end of the secondary cable. All transformers are supplied with color-coded cables. Two UV-resistant cable ties are also included for secure and easy mounting.

**Features:**

- Current ratios from 300 A (primary side) and 5 A (secondary side)
- No measuring cable interruption
- Ideal for use in very confined spaces
- Rapid mounting
- For use around insulated cables up to 28 mm diameter
- Compact and hinged
- Color-coded connecting cable 0.5 m

**Data**

**Technical data**

**Input – current transformer**

Primary rated current	300 A
Rated continuous thermal current $I_{cth}$	100 %
Rated short-time thermal current $I_{th}$	$60 \times I_N / 1 \text{ s}$
Rated surge current $I_{dyn}$	$2.5 \times I_{th}$
Rated frequency	50 ... 60 Hz

**Output – current transformer**

Secondary rated current	5 A
Rated power $S_r$	1 VA

**Measurement error**

Accuracy class	1
----------------	---

**Safety and protection**

Highest voltage for equipment $U_m$	AC 720 V <sub>rms</sub>
Protection type	IP20

**Test voltage**

Test voltage	AC 3 kV; 50 Hz; 1 min
--------------	-----------------------

Subject to changes. Please also observe the further product documentation!



## Connection data

Feedthrough for measurement conductor	Ø 28 mm
Cable type	2 x 1.5 mm <sup>2</sup> ; fine-stranded
Color code	black = S1; red = S2

## Physical data

Cable length	0.5 m
--------------	-------

## Mechanical data

Mounting type	Split-core current transformer (suspended)
---------------	--------------------------------------------

## Material data

Insulation class	E
Flammability class per UL94	V2
Housing material	PA 66
Weight	350 g

## Environmental requirements

Surrounding air temperature (operation)	-10 ... 55 °C
Surrounding air temperature (storage)	-20 ... 70 °C
Relative humidity	5 ... 85 % (without condensation)
Operating altitude (max.)	2000 m

## Standards and specifications

Conformity marking	CE
Standards/Specifications	EN 61869-1; EN 61869-2

## Commercial data

Packaging type	BOX
Country of origin	NL
GTIN	4055143950473
Customs tariff number	85043180888

Subject to changes. Please also observe the further product documentation!

## Compatible products

### General accessories



Item no.: 857-551

Current signal conditioner; Current input signal; Current and voltage output signal; Digital output;  
Configuration via software; Supply voltage: 24 VDC; 6 mm module width

[www.wago.com/857-551](http://www.wago.com/857-551)

## Downloads

### Documentation

#### Bid Text

X81 - Datei	xml 5.5 kB	Download
docx - Datei	docx 15.7 kB	Download

#### Instruction Leaflet

Kabelumbau-Stromwandler	V 1.1.0 15. 1. 2020	pdf 832.5 kB	Download
-------------------------	------------------------	-----------------	----------

## Engineering-Software

### Software for Interface-Products

WAGO Interface Configuration Software G2 FULL	1.0.5.03	exe	Download
The full setup, in addition to the WAGO Interface Configuration Software G2, includes the installation for the Microsoft .NET Framework.	14. 9. 2020	113.7 MB	
WAGO Interface Configuration Software G2 SMALL	1.0.5.03	exe	Download
The full setup only includes the WAGO Interface Configuration Software G2.	14. 9. 2020	29.8 MB	

## Environmental Product Compliance

### Compliance Search

Environmental Product Compliance 855-4105/300-101	URL	Download
Split-core current transformer; Primary rated current 300 A; Secondary rated current: 5 A; Rated power: 1 VA; Accuracy class: 1		

## Installation Notes

Subject to changes. Please also observe the further product documentation!

WAGO Kontakttechnik GmbH & Co. KG  
Hansastr. 27  
32423 Minden  
Phone: +49571 887-0 | Fax: +49571 887-169  
Email: [info.de@wago.com](mailto:info.de@wago.com) | Web: [www.wago.com](http://www.wago.com)

Do you have any questions about our products?  
We are always happy to take your call at +49 (571) 887-44222.

## Installation



Simple termination!



Quick and easy mounting!



Subject to changes. Please also observe the further product documentation!