

Antenna Datasheet

Product OC: YEMN518J1A

Version: 1.0

Date: 2024-06-17

Status: Released

Product Name: 5G & GNSS 5-in-1 Screw Combo Antenna

Key Features:

Optimized for 5G and 4G Networks

Φ 103.5 mm × 42.5 mm

4 × 4 5G/4G MIMO + GPS L1 & L5

Screw Mount-M18

SMA Male Connector

IP Rating: IP67 & IP69K

Compatible with ECE-R118 cables under demand

Overview

YEMN518J1A is a 5G & GNSS 5-in-1 combo antenna measuring Φ 103.5 mm $\times$ 42.5 mm. This ultra-wide-band 5G & GNSS antenna provides broad coverage from 600–6,000 MHz whilst offering backward-compatibility to support 4G, 3G and 2G networks as well as LTE Cat-M and narrowband IoT (NB-IoT). The antenna is available with connection via 5 cable lengths from 300–5,000 mm, terminated with SMA Male connectors. Ideal for applications where the antenna is required to be discrete this low profile, screw mount omni-directional antenna, is easy to install with maximum durability assured thanks to its IP67 & IP69K and IK09 rated enclosure. It is compatible with Quectel's RM520x Series modules.

YEMN518J1A has 2 $\times$ 5G LMH antennas, 2 $\times$ 5G MH/Wi-Fi antennas and 1 $\times$ GNSS L1 & L5 antenna. It allows high efficiency, stable signal transmission and reception for active GNSS from 1164–1189 MHz & 1565–1606 MHz, and 5G/4G bands from 600–960 MHz and 1400–6000 MHz. In the meantime, this product also offers high isolation between antennas to avoid self-interference. All in all, this unique product is designed to provide stable and high-speed data connection to 5G & GNSS applications. The YEMN518J1A can be used in harsh environments thanks to its robust UV resistant (UL 746c f1) and flame resistant (UL 94 V-0) enclosure.

Typical Applications Include:

- Smart Utilities and Buildings
- Digital Signage
- Warehouses & Logistic systems
- Industrial factory automation, robotic machinery and other M2M systems
- Transport (Busses, Utility & Public Safety)
- Mining Vehicles & Machinery communications, telemetry and automation

Quectel provides comprehensive antenna design support such as simulation, testing and manufacturing for custom antenna solutions to meet your specific application needs. We have regional R & D centers to offer quick response to meet your requirements. Please contact our sales & FAEs if you have any requests.

Contents

Overview.....	1
Contents	2
1 Specification.....	3
1.1 Electrical.....	3
1.1.1 LMHs	3
1.1.2 MHs	4
1.1.3 GNSS	6
1.2 Mechanical & Environment	7
1.3 Supported Bands	8
1.4 Block Diagram (Active Antenna)	12
2 Drawing	13
3 Detailed Performance	14
3.1 S-Parameter Test	14
3.1.1 VSWR.....	14
3.1.2 Return Loss	17
3.1.3 Isolation	20
3.1.3.1 Test Status: In Free Space	20
3.1.3.2 Test Status: On 320 mm × 240 mm Metal Plane	22
3.1.4 GNSS LNA Gain.....	25
3.1.5 GNSS Noise Figure.....	26
3.2 Radiation Performance Test.....	27
3.2.1 Efficiency	27
3.2.2 Average Gain	30
3.2.3 Peak Gain.....	32
3.2.4 3D & 2D Radiation Pattern.....	35
3.2.4.1 Test Status: In Free Space	35
3.2.4.2 Test Status: On 320 × 240 mm Metal Plane	51
4 Packaging	66
Contact Us.....	68
Legal Notices	69
Revision History	71

1 Specification

Test Condition: In Free Space & On 320 mm × 240 mm Metal Plane

1.1 Electrical

Electrical Specifications		
Frequency Range	LMHs	600–960 MHz, 1400–6000 MHz
	MHs	1400–6000 MHz
	GNSS	1164–1189 MHz, 1565–1606 MHz
Radiation Pattern	LMHs & MHs	Omni-directional
	GNSS	Directional
Polarization	LMHs & MHs	Linear
	GNSS	RHCP
Impedance		50 Ω
Isolation		≤ -6.9 dB

1.1.1 LMHs

Band	Band	B71	B12 /B13 /B28	B5 /B8 /B26	n74 /n75 /n76	B1 /B2 /B3	B40	Wi-Fi 2G	B38 /B41	B42 /B48 /n77	n79	Wi-Fi 5G
SPEC	Freq. (MHz)	600– 700	700– 810	820– 960	1420– 1520	1700– 2170	2300– 2400	2400– 2500	2500– 2690	3300– 4200	4400– 5000	5150– 5850
Max VSWR	FS	9.5	2.4	5.7	2.0	1.4	1.4	1.3	1.3	2.5	1.9	1.7
	MP	8.5	3.7	5.3	2.1	1.9	1.6	1.5	1.4	2.8	2.0	1.9
Max	FS	-1.8	-7.7	-3.1	-9.5	-15.6	-15.6	-17.7	-17.7	-7.4	-10.2	-11.7

Return Loss (dB)	MP	-2.1	-4.8	-3.3	-9.0	-10.2	-12.7	-14.0	-15.6	-6.5	-9.5	-10.2
AVG Eff. (%)	FS	20.9	37.2	28.8	55.2	69.8	73.9	73.3	66.6	60.4	55.2	46.7
	MP	14.0	39.0	34.7	50.0	64.7	60.4	64.9	57.4	48.0	48.2	44.2
AVG AVG Gain (dB)	FS	-7.1	-4.4	-5.6	-2.6	-1.6	-1.3	-1.3	-1.8	-2.2	-2.6	-3.3
	MP	-9.0	-4.2	-4.7	-3.1	-1.9	-2.2	-1.9	-2.4	-3.3	-3.2	-3.5
Max Peak Gain (dBi)	FS	-1.7	0.5	0.1	1.6	2.0	1.6	2.0	2.5	5.0	3.9	3.7
	MP	-2.5	2.7	2.3	4.6	5.9	4.8	5.5	5.5	6.2	5.3	4.6
VSWR	FS	≤ 9.2										
	MP	≤ 8.5										
Return Loss	FS	≤ -1.9 dB										
	MP	≤ -2.0 dB										
Peak Gain	FS	≤ 5.0 dBi										
	MP	≤ 6.2 dBi										

- LMHs: LMH Antennas (LMH1, LMH2)
- MHs: MH Antennas (MH1, MH2)
- FS: In Free Space
- MP: On 320 mm × 240 mm Metal Plane

1.1.2 MHs

Band	Band	B71	B12 /B13 /B28	B5 /B8 /B26	n74 /n75 /n76	B1 /B2 /B3	B40	Wi-Fi 2G	B38 /B41	B42 /B48 /n77	n79	Wi-Fi 5G
	Freq. (MHz)	600–700	700–810	820–960	1420–1520	1700–2170	2300–2400	2400–2500	2500–2690	3300–4200	4400–5000	5150–5850
Max VSWR	FS	-	-	-	4.0	2.8	3.8	3.3	2.9	1.9	2.2	2.4
	MP	-	-	-	2.9	2.4	4.3	4.4	3.2	2.3	3.0	2.3
Max Return Loss (dB)	FS	-	-	-	-4.5	-6.5	-4.7	-5.4	-6.2	-9.9	-8.3	-7.6
	MP	-	-	-	-6.2	-7.6	-4.1	-4.0	-5.6	-8.3	-6.1	-8.1
AVG Eff.	FS	-	-	-	48.7	55.7	38.0	37.0	42.1	63.0	51.8	49.2

(%)	MP	-	-	-	39.7	60.0	36.2	34.4	39.8	64.4	45.9	53.1
AVG AVG	FS	-	-	-	-3.2	-2.6	-4.2	-4.4	-3.8	-2.0	-2.9	-3.1
Gain (dB)	MP	-	-	-	-4.1	-2.2	-4.4	-4.6	-4.0	-1.9	-3.4	-2.8
Max Peak	FS	-	-	-	1.2	2.5	1.2	3.2	3.5	4.9	4.4	4.9
Gain (dBi)	MP	-	-	-	3.9	6.7	2.8	2.8	4.1	8.2	3.9	5.8
VSWR	FS	≤ 4.0										
	MP	≤ 4.4										
Return Loss	FS	≤ -4.5 dB										
	MP	≤ -4 dB										
Peak Gain	FS	≤ 4.9 dBi										
	MP	≤ 8.2 dBi										

- LMHs: LMH Antennas (LMH1, LMH2)
- MHs: MH Antennas (MH1, MH2)
- FS: In Free Space
- MP: On 320 mm × 240 mm Metal Plane

1.1.3 GNSS

Band	GPS L5							
	GALILEO E5a	GALILEO E5b	GPS L2 QZSS L2C	GLONASS G2	BDS B3	BDS B1I	GPS L1 GALILEO E1	GLONASS G1
Frequency (MHz)	1176	1207	1227	1248	1268	1561	1575	1602
VSWR	1.61						1.52	1.49
Return Loss (dB)	-12.8						-13.6	-14
Efficiency (%)	47						42	40
Peak Gain (dBi)	-0.04						-1.49	-1.17

LNA Electrical	
LNA Gain	28 ±3 dB
Noise Figure	≤ 2.5 dB
Output VSWR	< 2.0
Filter Out-of-Band Attenuation	65 dB f0 ±100 MHz f0 (1176 MHz, 1588 MHz)
Working Voltage	DC 2–5 V
Working Current	12.3 ±3 mA
Impedance	50 Ω

1.2 Mechanical & Environment

Mechanical		
Antenna Size		Φ 103.5 mm × 42.5 mm
Casing Material & Color		PC & Black
Cable Type & Length	LMHs & MHs	RG405 Black & 300 mm
	GNSS	RG174 Black & 300 mm
Connector Type		SMA Male (The current state of the SMA connector is not waterproof. If a waterproof connector is required, it can be customized.)
Weight		Typ. 220 g
Mounting Type		Screw Mounting (M18)
Environmental		
Operation Temperature		-40 °C to +85 °C
Storage Temperature		-40 °C to +85 °C
Ingress Protection (IP) Rating		IP67 (After Installation) IP69K (After Installation)
Impact Protection (IK) Rating		IK09
RoHS & REACH Compliant		Yes
Housing Flame Rating		UL 94 V-0
Housing UV Resistant		UL 746c f1

- LMHs: LMH Antennas (LMH1, LMH2)
- MHs: MH Antennas (MH1, MH2)
- FS: In Free Space
- MP: On 320 mm × 240 mm Metal Plane


1.3 Supported Bands

5G NR/ LTE/ LTE-Advanced/ WCDMA/ HSPA/ HSPA+/ GPRS/ GSM/ NB-IoT					
Band	Frequency (MHz)	Uplink (MHz)	Downlink (MHz)	LMHs	MHs
1	2100	1920–1980	2110–2170	√	√
2	1900	1850–1910	1930–1990	√	√
3	1800	1710–1785	1805–1880	√	√
4	1700	1710–1755	2110–2155	√	√
5	850	824–849	869–894	√	-
7	2600	2500–2570	2620–2690	√	√
8	900	880–915	925–960	√	-
9	1800	1749.9–1784.9	1844.9–1879.9	√	√
11	1500	1427.9–1447.9	1475.9–1495.9	√	√
12	700	699–716	729–746	√	-
13	700	777–787	746–756	√	-
14	700	788–798	758–768	√	-
17	700	704–716	734–746	√	-
18	850	815–830	860–875	√	-
19	850	830–845	875–890	√	-
20	800	832–862	791–821	√	-
21	1500	1447.9–1462.9	1495.9–1510.9	√	√
22	3500	3410–3490	3510–3590	√	√
23	2100	2000–2020	2180–2200	√	√
24	1600	1626.5–1660.5	1525–1559	√	√
25	1900	1850–1915	1930–1995	√	√
26	850	814–849	859–894	√	-


5G NR/ LTE/ LTE-Advanced/ WCDMA/ HSPA/ HSPA+/ GPRS/ GSM/ NB-IoT					
Band	Frequency (MHz)	Uplink (MHz)	Downlink (MHz)	LMHs	MHs
28	700	703–748	758–803	√	-
31	450	452.5–457.5	462.5–467.5	-	-
34	2100	2010–2025		√	√
38	2600	2570–2620		√	√
39	1900	1880–1920		√	√
40	2300	2300–2400		√	√
41	2500	2496–2690		√	√
42	3500	3400–3600		√	√
48	3500	3550–3700		√	√
66	1700	1710 - 1780	2110 - 2200	√	√
71	600	663 - 698	617 - 652	√	-
74	1500	1427 - 1470	1475 - 1518	√	√
77	3500	3300 - 4200		√	√
78	3500	3300 - 3800		√	√
79	4500	4400 - 5000		√	√
Note: Covered √ means efficiency > 20 %					

GNSS Frequency Bands (MHz)					
GPS	L1 Centre 1575.42 (1565–1586)	L2 Centre 1227.6 (1217–1238)	L5 Centre 1176.45 (1164–1189)		
	√	-	√		
GLONASS	G1-L10C-L10F Centre 1601 (1595–1606)	G2-L20C-L20F Centre 1248.06 (1241–1255)	G3-L30C Centre 1202.025 (1189–1213)		
	√	-	-		
GALILEO	E1 Centre 1575.42 (1563–1588)	E5a Centre 1176.45 (1166–1187)	E5b Centre 1207.14 (1197–1218)	E6 Centre 1278.75 (1258–1300)	
	√	√	-	-	
BDS	B1I Centre 1561.098 (1559–1564)	B1C (BDS-3) Centre 1575.42 (1559–1592)	B2a-B2I Centre 1176.45 (1166–1187)	B2b Centre 1207.14 (1197–1217)	B3 Centre 1268.52 (1258–1279)
		√	√	-	-
QZSS	L1 Centre 1575.42 (1573–1578)	L2C Centre 1227.6 (1226–1229)	L5 Centre 1176.45 (1166–1187)	L6 Centre 1278.75 (1257–1300)	
	√	-	√	-	
IRNSS	L5 Centre 1176.45 (1164–1189)				
	√				


GNSS Bands and Constellations




1.4 Block Diagram (Active Antenna)



2 Drawing





- Description of tube color and character color:
GNSS: blue tube + white character
LMH: red tube + white character
MH: black tube + white character
- LMHs and MHs can be connected arbitrarily.
- Recommended assembly hole diameter: 19.0 mm.
- Recommended mounting plane thickness: 2.0–15mm.



3 Detailed Performance

3.1 S-Parameter Test

3.1.1 VSWR




VSWR - LMHs

Frequency (MHz)		600	630	710	830	900	960	1440	1710	1740	1880
LMH1	FS	9.2	6.2	1.6	1.5	3.7	5.2	2.0	1.2	1.2	1.1
	MP	4.2	4.2	3.2	2.7	4.6	5.3	1.9	1.3	1.3	1.3
LMH2	FS	9.5	6.6	2.1	2.6	4.7	5.7	1.8	1.2	1.2	1.3
	MP	8.5	6.3	3.5	2.4	4.4	5.1	2.0	1.4	1.4	1.7
Frequency (MHz)		1950	2140	2350	2450	2600	3600	4700	5000	5500	6000
LMH1	FS	1.2	1.4	1.4	1.3	1.0	1.2	1.4	1.4	1.2	2.2
	MP	1.5	1.6	1.5	1.6	1.1	1.3	1.4	1.4	1.5	2.5
LMH2	FS	1.4	1.5	1.4	1.2	1.1	1.0	1.6	1.5	1.4	2.0
	MP	1.8	1.7	1.5	1.5	1.2	1.2	1.5	1.5	1.7	2.1

VSWR - MHs



Frequency (MHz)		600	630	710	830	900	960	1440	1710	1740	1880
MH1	FS	-	-	-	-	-	-	4.0	1.6	1.4	1.1
	MP	-	-	-	-	-	-	1.9	1.4	1.5	1.1
MH2	FS	-	-	-	-	-	-	3.8	2.0	2.0	1.1
	MP	-	-	-	-	-	-	2.0	1.9	1.4	1.2
Frequency (MHz)		1950	2140	2350	2450	2600	3600	4700	5000	5500	6000
MH1	FS	1.3	2.7	3.5	3.2	2.5	1.4	1.7	1.5	2.1	2.0
	MP	1.2	2.2	3.3	3.9	2.9	1.9	2.3	1.4	2.1	1.7
MH2	FS	1.2	2.7	3.8	3.3	2.7	1.6	2.1	1.5	2.2	1.5
	MP	1.1	2.9	4.1	3.3	2.5	2.0	2.4	1.7	2.0	1.4



VSWR - GNSS

Frequency (MHz)	1176	1207	1227	1248	1268	1561	1575	1602
VSWR	1.61						1.52	1.49

3.1.2 Return Loss




Return Loss (dB) - LMHs

Frequency (MHz)		600	630	710	830	900	960	1440	1710	1740	1880
LMH1	FS	-1.9	-2.8	-12.8	-13.4	-4.8	-3.4	-9.8	-21.3	-20.9	-31.7
	MP	-4.2	-4.2	-5.6	-6.6	-3.9	-3.3	-10.1	-18.5	-16.8	-16.7
LMH2	FS	-1.8	-2.6	-9.0	-6.9	-3.8	-3.1	-11.0	-19.2	-19.4	-17.0
	MP	-2.0	-2.8	-5.1	-7.9	-4.0	-3.5	-9.6	-15.1	-14.8	-12.1
Frequency (MHz)		1950	2140	2350	2450	2600	3600	4700	5000	5500	6000
LMH1	FS	-20.5	-15.7	-16.4	-17.4	-33.5	-21.1	-15.9	-16.2	-20.2	-8.6
	MP	-14.5	-12.7	-13.5	-13.1	-23.7	-18.1	-14.9	-15.7	-13.5	-7.3
LMH2	FS	-16.1	-14.5	-16.1	-19.2	-25.1	-33.1	-12.5	-14.0	-16.3	-9.3
	MP	-10.5	-11.5	-14.4	-13.4	-20.2	-20.0	-14.0	-14.1	-11.9	-9.1

Return Loss (dB) - MHs

Frequency (MHz)		600	630	710	830	900	960	1440	1710	1740	1880
MH1	FS	-	-	-	-	-	-	-4.4	-12.7	-15.6	-26.4
	MP	-	-	-	-	-	-	-10.2	-15.6	-14.0	-26.4
MH2	FS	-	-	-	-	-	-	-4.7	-9.5	-9.5	-26.4
	MP	-	-	-	-	-	-	-9.5	-10.2	-15.6	-20.8
Frequency (MHz)		1950	2140	2350	2450	2600	3600	4700	5000	5500	6000
MH1	FS	-17.7	-6.8	-5.1	-5.6	-7.4	-15.6	-11.7	-14.0	-9.0	-9.5
	MP	-20.8	-8.5	-5.4	-4.6	-6.2	-10.2	-8.1	-15.6	-9.0	-11.7
MH2	FS	-20.8	-6.8	-4.7	-5.4	-6.8	-12.7	-9.0	-14.0	-8.5	-14.0
	MP	-26.4	-6.2	-4.3	-5.4	-7.4	-9.5	-7.7	-11.7	-9.5	-15.6




Return Loss (dB) - GNSS

Frequency (MHz)	1176	1207	1227	1248	1268	1561	1575	1602
Return Loss (dB)	-12.8	-	-	-	-	-	-13.6	-14


3.1.3 Isolation

3.1.3.1 Test Status: In Free Space


3.1.3.1.1 LMH1




3.1.3.1.2 LMH2



3.1.3.1.3 MH1




3.1.3.1.4 MH2




3.1.3.2 Test Status: On 320 mm × 240 mm Metal Plane


3.1.3.2.1 LMH1




3.1.3.2.2 LMH2



3.1.3.2.3 MH1



3.1.3.2.4 MH2




- FS: In Free Space
- MP: On 320 mm × 240 mm Metal Plane

Max Isolation (dB)

	Band	B71	B12/ B13/ B28	B5/ B8/ B26	n74/ n75/ n76	B1/ B2/ B3	B40	Wi-Fi 2G	B38/ B41	B42/ B48/ n77	n79	Wi-Fi 5G
	Freq. (MHz)	600– 700	700– 810	820– 960	1420– 1520	1700– 2170	2300– 2400	2400– 2500	2500– 2690	3300– 4200	4400– 5000	5150– 5850
LMH1	FS	-12.7	-7.2	-7.2	-7.5	-7.7	-11.4	-10.5	-6.9	-11.7	-10.7	-12.7
	MP	-14.1	-9.0	-8.6	-8.3	-8.7	-12.0	-10.8	-8.5	-10.6	-10.5	-14.3
LMH2	FS	-12.7	-7.8	-8.8	-7.2	-8.2	-13.1	-11.4	-8.2	-12.6	-11.8	-12.1
	MP	-13.3	-9.9	-8.7	-8.7	-9.4	-13.1	-11.6	-10.0	-12.0	-11.9	-11.3
MH1	FS	-12.8	-7.8	-8.8	-7.5	-7.7	-11.4	-10.5	-6.9	-11.7	-10.7	-12.7
	MP	-13.3	-9.9	-8.7	-8.3	-8.7	-12.0	-10.8	-8.5	-10.6	-10.5	-14.3
MH2	FS	-13.1	-7.2	-7.2	-7.2	-8.2	-13.1	-11.4	-8.2	-12.6	-11.8	-12.1
	MP	-13.5	-9.0	-8.6	-8.7	-9.4	-13.1	-11.6	-10.0	-12.0	-11.9	-11.3

- FS: In Free Space
- MP: On 320 mm × 240 mm Metal Plane


3.1.4 GNSS LNA Gain



LNA Gain (dB)

Frequency (MHz)	1176	1207	1227	1248	1268	1561	1575	1602
LNA Gain (dB)	29.3	-	-	-	-	-	28.1	27.9

3.1.5 GNSS Noise Figure





Noise Figure (dB)

Frequency (MHz)	1176	1207	1227	1248	1268	1561	1575	1602
Noise Figure (dB)	2.02	-	-	-	-	-	1.95	2.23

3.2 Radiation Performance Test

3.2.1 Efficiency




Efficiency (%) - LMHs

Frequency (MHz)		600	630	710	830	900	960	1440	1710	1740	1880
LMH1	FS	10.5	15.4	30.8	44.1	22.9	21.7	54.1	62.2	65.4	69.3
	MP	6.1	9.1	27.5	48.6	28.1	29.9	41.5	60.9	64.5	60.9
LMH2	FS	11.3	18.1	39.2	45.9	23.3	22.2	46.6	65.7	69.3	62.1
	MP	4.9	9.1	21.4	51.1	27.6	29.1	37.2	65.8	68.2	62.5
Frequency (MHz)		1950	2140	2350	2450	2600	3600	4700	5000	5500	6000
LMH1	FS	72.4	75.4	75.5	73.0	67.3	66.4	56.4	46.7	45.5	37.2
	MP	65.5	66.6	59.3	64.8	57.5	60.9	50.4	43.3	43.7	30.6
LMH2	FS	71.1	75.4	73.3	66.1	65.8	60.1	57.6	49.0	53.6	40.2
	MP	70.1	69.8	68.0	69.5	70.0	65.7	56.3	45.3	45.1	35.3

Efficiency (%) - MHs



Frequency (MHz)		600	630	710	830	900	960	1440	1710	1740	1880
MH1	FS	-	-	-	-	-	-	54.1	63.7	56.6	63.4
	MP	-	-	-	-	-	-	46.4	60.7	66.3	60.9
MH2	FS	-	-	-	-	-	-	36.1	56.4	61.9	58.3
	MP	-	-	-	-	-	-	44.9	70.9	70.6	61.0
Frequency (MHz)		1950	2140	2350	2450	2600	3600	4700	5000	5500	6000
MH1	FS	59.9	51.5	40.6	35.0	40.6	66.8	54.9	45.2	48.9	47.6
	MP	63.3	47.3	36.0	33.5	40.8	66.9	44.1	46.4	53.2	60.2
MH2	FS	65.5	42.7	35.5	37.2	45.7	67.5	44.4	37.1	38.1	40.8
	MP	69.4	49.8	34.7	30.6	53.0	58.1	46.4	44.3	44.7	53.9



Efficiency (%) - GNSS

Frequency (MHz)	1176	1207	1227	1248	1268	1561	1575	1602
Efficiency (%)	47	-	-	-	-	-	42	40

3.2.2 Average Gain





Average Gain (dB) - LMHs

Frequency (MHz)		600	630	710	830	900	960	1440	1710	1740	1880
LMH1	FS	-9.8	-8.1	-5.1	-3.6	-6.4	-6.6	-2.7	-2.1	-1.8	-1.6
	MP	-12.1	-10.4	-5.6	-3.1	-5.5	-5.3	-3.8	-2.2	-1.9	-2.2
LMH2	FS	-9.5	-7.4	-4.1	-3.4	-6.3	-6.6	-3.3	-1.8	-1.6	-2.1
	MP	-13.1	-10.4	-6.7	-2.9	-5.6	-5.4	-4.3	-1.8	-1.7	-2.0
Frequency (MHz)		1950	2140	2350	2450	2600	3600	4700	5000	5500	6000
LMH1	FS	-1.4	-1.2	-1.2	-1.4	-1.7	-1.8	-2.5	-3.3	-3.4	-4.3
	MP	-1.8	-1.8	-2.3	-1.9	-2.4	-2.2	-3.0	-3.6	-3.6	-5.1
LMH2	FS	-1.5	-1.2	-1.4	-1.8	-1.8	-2.2	-2.4	-3.1	-2.7	-4.0
	MP	-1.5	-1.6	-1.7	-1.6	-1.6	-1.8	-2.5	-3.4	-3.5	-4.5

Average Gain (dB) - MHs

Frequency (MHz)		600	630	710	830	900	960	1440	1710	1740	1880
MH1	FS	-	-	-	-	-	-	-2.7	-2.0	-2.5	-2.0
	MP	-	-	-	-	-	-	-3.3	-2.2	-1.8	-2.2
MH2	FS	-	-	-	-	-	-	-4.4	-2.5	-2.1	-2.3
	MP	-	-	-	-	-	-	-3.5	-1.5	-1.5	-2.1
Frequency (MHz)		1950	2140	2350	2450	2600	3600	4700	5000	5500	6000
MH1	FS	-2.2	-2.9	-3.9	-4.6	-3.9	-1.8	-2.6	-3.5	-3.1	-3.2
	MP	-2.0	-3.3	-4.4	-4.7	-3.9	-1.7	-3.6	-3.3	-2.7	-2.2
MH2	FS	-1.8	-3.7	-4.5	-4.3	-3.4	-1.7	-3.5	-4.3	-4.2	-3.9
	MP	-1.6	-3.0	-4.6	-5.1	-2.8	-2.4	-3.3	-3.5	-3.5	-2.7

3.2.3 Peak Gain




Peak Gain (dBi) - LMHs

Frequency (MHz)		600	630	710	830	900	960	1440	1710	1740	1880
LMH1	FS	-5.6	-4.1	-1.8	-0.1	-3.7	-3.6	1.6	1.7	2.0	1.3
	MP	-7.4	-6.4	-2.1	2.2	0.6	1.7	3.0	4.6	5.0	4.6
LMH2	FS	-3.3	-2.3	0.3	0.2	-3.4	-2.8	1.6	1.8	2.2	1.6
	MP	-8.4	-6.2	-2.9	3.0	0.1	1.0	1.5	4.0	4.1	5.6
Frequency (MHz)		1950	2140	2350	2450	2600	3600	4700	5000	5500	6000
LMH1	FS	1.1	1.0	1.2	1.9	2.2	3.9	2.6	3.2	2.4	0.8
	MP	3.5	5.3	4.6	4.4	3.0	4.5	2.6	4.4	4.2	2.7
LMH2	FS	2.0	1.8	2.7	3.2	2.7	2.2	4.6	2.2	1.8	2.3
	MP	4.5	4.4	4.0	3.4	3.8	5.6	3.0	2.4	3.7	3.9

Peak Gain (dBi) - MHs

Frequency (MHz)		600	630	710	830	900	960	1440	1710	1740	1880
MH1	FS	-	-	-	-	-	-	1.1	2.4	1.8	2.3
	MP	-	-	-	-	-	-	3.8	4.2	4.9	6.0
MH2	FS	-	-	-	-	-	-	-0.1	0.9	0.8	1.4
	MP	-	-	-	-	-	-	4.3	5.0	4.4	5.3
Frequency (MHz)		1950	2140	2350	2450	2600	3600	4700	5000	5500	6000
MH1	FS	1.7	1.0	0.7	0.7	1.2	4.0	3.3	2.4	4.5	4.6
	MP	4.1	3.9	2.0	2.4	2.3	6.5	2.7	3.9	4.9	6.0
MH2	FS	2.1	0.9	0.5	2.0	2.1	6.0	5.3	2.7	6.1	7.0
	MP	4.3	3.0	1.7	0.9	4.0	5.8	2.9	4.5	4.7	7.4




Peak Gain (dBi)

Frequency (MHz)	1176	1207	1227	1248	1268	1561	1575	1602
Peak Gain (dBi)	-0.04	-	-	-	-	-	-1.49	-1.17



3.2.4 3D & 2D Radiation Pattern

3.2.4.1 Test Status: In Free Space









● **LMH1**









630 MHz





710 MHz




830 MHz

















● **LMH2**









630 MHz





710 MHz




830 MHz













● **MH1**









● **MH2**









● **GNSS**


1176 MHz




Phi=0 Freq=1176MHz




1575 MHz




Phi=0 Freq=1575MHz




Phi=90 Freq=1176MHz




Theta=90 Freq=1176MHz




Phi=90 Freq=1575MHz




Theta=90 Freq=1575MHz




1602 MHz




Phi=0 Freq=1602MHz




Phi=90 Freq=1602MHz





Theta=90 Freq=1602MHz









3.2.4.2 Test Status: On 320 × 240 mm Metal Plane

● **LMH1**









630 MHz





710 MHz




830 MHz

















● **LMH2**



630 MHz









710 MHz





830 MHz




900 MHz













● **MH1**









● **MH2**









4 Packaging

Step	Packaging Picture / 2D Picture	Description
1		Put the product in a PE bag inside the inner box.
2		Top the product with the pearl cotton.

		Inner box diagram <u>Inner Box Size:</u> $L \times W \times H = 191 \times 191 \times 175 \text{ mm}$
3		(6 Inner Boxes / Carton Box) (6 PCS Antennas / Carton Box) <u>Carton Size:</u> $L \times W \times H = 606 \times 410 \times 218 \text{ mm}$
4		Position for Attaching Labels ① Carton Label ② Quality Label
5		Sealing Cartons “工” type sealing cartons

Contact Us

At Quectel, our aim is to provide timely and comprehensive services to our customers. If you require any assistance, please contact our headquarters:

Quectel Wireless Solutions Co., Ltd.

Building 5, Shanghai Business Park Phase III (Area B), No.1016 Tianlin Road, Minhang District, Shanghai 200233, China

Tel: +86 21 5108 6236

Email: info@quectel.com

Or our local offices. For more information, please visit:

[http: www.quectel.com-support-sales.htm](http://www.quectel.com-support-sales.htm)

For technical support, or to report documentation errors, please visit:

[http: www.quectel.com-support-technical.htm](http://www.quectel.com-support-technical.htm)

Or email us at: support@quectel.com

Legal Notices

We offer information as a service to you. The provided information is based on your requirements and we make every effort to ensure its quality. You agree that you are responsible for using independent analysis and evaluation in designing intended products, and we provide reference designs for illustrative purposes only. Before using any hardware, software or service guided by this document, please read this notice carefully. Even though we employ commercially reasonable efforts to provide the best possible experience, you hereby acknowledge and agree that this document and related services hereunder are provided to you on an “as available” basis. We may revise or restate this document from time to time at our sole discretion without any prior notice to you.

Use and Disclosure Restrictions

License Agreements

Documents and information provided by us shall be kept confidential, unless specific permission is granted. They shall not be accessed or used for any purpose except as expressly provided herein.

Copyright

Our and third-party products hereunder may contain copyrighted material. Such copyrighted material shall not be copied, reproduced, distributed, merged, published, translated, or modified without prior written consent. We and the third party have exclusive rights over copyrighted material. No license shall be granted or conveyed under any patents, copyrights, trademarks, or service mark rights. To avoid ambiguities, purchasing in any form cannot be deemed as granting a license other than the normal non-exclusive, royalty-free license to use the material. We reserve the right to take legal action for noncompliance with abovementioned requirements, unauthorized use, or other illegal or malicious use of the material.

Trademarks

Except as otherwise set forth herein, nothing in this document shall be construed as conferring any rights to use any trademark, trade name or name, abbreviation, or counterfeit product thereof owned by Quectel or any third party in advertising, publicity, or other aspects.

Third-Party Rights

This document may refer to hardware, software and-or documentation owned by one or more third parties (“third-party materials”). Use of such third-party materials shall be governed by all restrictions and obligations applicable thereto.

We make no warranty or representation, either express or implied, regarding the third-party materials, including but not limited to any implied or statutory, warranties of merchantability or fitness for a particular purpose, quiet enjoyment, system integration, information accuracy, and non-infringement of any third-party intellectual property rights with regard to the licensed technology or use thereof. Nothing herein constitutes a representation or warranty by us to either develop, enhance, modify, distribute, market, sell, offer for sale, or otherwise LMHtain production of any our products or any other hardware, software, device, tool, information, or product. We moreover disclaim any and all warranties arising from the course of dealing or usage of trade.

Privacy Policy

To implement module functionality, certain device data are uploaded to Quectel's or third-party's servers, including carriers, chipset suppliers or customer-designated servers. Quectel, strictly abiding by the relevant laws and regulations, shall retain, use, disclose or otherwise process relevant data for the purpose of performing the service only or as permitted by applicable laws. Before data interaction with third parties, please be informed of their privacy and data security policy.

Disclaimer

- a) We acknowledge no liability for any injury or damage arising from the reliance upon the information.
- b) We shall bear no liability resulting from any inaccuracies or omissions, or from the use of the information contained herein.
- c) While we have made every effort to ensure that the functions and features under development are free from errors, it is possible that they could contain errors, inaccuracies, and omissions. Unless otherwise provided by valid agreement, we make no warranties of any kind, either implied or express, and exclude all liability for any loss or damage suffered in connection with the use of features and functions under development, to the maximum extent permitted by law, regardless of whether such loss or damage may have been foreseeable.
- d) We are not responsible for the accessibility, safety, accuracy, availability, legality, or completeness of information, advertising, commercial offers, products, services, and materials on third-party websites and third-party resources.

Copyright © Quectel Wireless Solutions Co., Ltd. 2024. All rights reserved.

Revision History

Version	Date	Author	Note
-	2024-06-17	Mordecai LIU/ Lance SUN/ Junsen LI/ David LIU/ Aria CHU	Creation of the document
1.0	2024-06-17	Mordecai LIU/ Lance SUN/ Junsen LI/ David LIU/ Aria CHU	First official release



www.quectel.com