

# ALPHA<sup>®</sup> FLUITIN 1532

No Clean, Flux Cored Wire Solder

J-STD-004-ROM1/ IPC-TM-650 2.6.3.3 / ISO 1224-1.1.2 / DIN 8511-F-SW26

# DESCRIPTION

**ALPHA Fluitin 1532** is an activated rosin cored solder wire developed for general hand soldering applications. The unique activator system offers good thermal stability at pre-soldering temperatures ensuring that **ALPHA Fluitin 1532** performs extremely well on parts and surfaces which present poor or difficult soldering conditions.

**ALPHA Fluitin 1532** leaves post-soldering residues that are hard and which can be safely left without the need to remove them. If the removal of residues is required, then semi-aqueous or aqueous systems can be used effectively.

# READ ENTIRE TECHNICAL DATA SHEET BEFORE USING THIS PRODUCT

# **FEATURES & BENEFITS**

Features	Benefits	
Very fast wetting	Low cycle times for component touch-up and manual assembly	
Good spread characteristics	Excellent solder joints	
Pleasant pine smell	Operator friendly	
Clear and safe residue	No-clean residues, useful for all applications	
Provides good joint appearance	Makes inspection easy	

ALPHA Fluitin 1532 is suitable for use in any commercial no-clean hand soldering application that specifies compliance to J-STD-004 – ROM1 standard. It is suited to such areas of industry (subject to the above criteria) as TV, Audio equipment, Video/DVD, Games box and all types of household appliances.





# **PRODUCT INFORMATION**

		Melting or Solidus	
Standard	Alloy Designation	/ Liquidus Temp °C	Flux Amount
ISO 9453	SAC305	217 / 221	2.2% & 3.3%
Proprietary	SACX Plus <sup>®</sup> 0307	217 / 228	2.2% & 3.3%
ISO 9453	Sn99/Cu1	227 / ~235	2.2% & 3.3%
ISO 9453	Sn50/Pb50	183 to 216	2.2%
ISO 9453	Sn60/Pb40	183 to 190	1.4% & 2.2%
ISO 9453	Sn60/Pb38/Cu2	183 to 190	1.1% & 2.2%
ISO 9453	Sn62/Pb36/Ag2	178 to 190	2.2%
ISO 9453	Sn63/Pb37	183	1.1% & 2.2%

\* Fluitin 1532 may also be available in other alloys and flux amounts on request.

## **APPLICATION GUIDELINES**

A soldered joint is formed by heating the parts to be soldered to a temperature in excess of the melting point of the alloy to be used – in hand soldering this is how a soldering iron is used. By feeding the cored wire onto the parts, the flux is able to flow and remove oxidized metal, while the solder creates a thin inter-metallic bond which becomes the solder joint. ALPHA Fluitin 1532 is also ideal for robotic soldering applications.

Note the following tips:

- Use a soldering iron tip size and form to suit the operation: small tips for soldering large components may prevent the formation of a joint or slow the process down.
- Select a solder wire diameter to suit both the soldering iron tip and the parts/components to be soldered.
- Soldering iron systems should provide sufficient heat to satisfy the requirements of the points above.
- A typical solder tip temperature would be between 120 °C and 160 °C above the liquidus temperature of the alloy. The ideal temperature to use is dependent on how thermally demanding the assembly is.
- Cored solder wires can be provided in different grades of alloy so always ensures that you have selected the right grade for the application.





• Do not overheat as this causes an increase in the depth of the inter-metallic layer, which in turn weakens the joint.

If you choose to use a liquid rework flux, ALPHA 615 Flux is recommended to maintain high electrical reliability. ALPHA 615 flux is available in ALPHA's 'Write Flux Pens' for precision flux application.

# TECHNICAL DATA

Physical Properties	Тур	ical Values	
Rosin grade	WW per Fed Spec. LL	WW per Fed Spec. LL-R-626	
Rosin Softening Point	71 °C (160 °F)	71 °C (160 °F)	
Acid Value	170 to 190 mg KOH/g	170 to 190 mg KOH/g flux (IPC-TM-650-2.3.13)	
Halide Content	0.80 to 1.10% weight (	0.80 to 1.10% weight (IPC-TM-650-2.3.28.1)	
Copper Mirror	<50% breakthrough pe	<50% breakthrough per IPC J-STD-004A	
	ROM1 per IPC J-STD-	ROM1 per IPC J-STD-004A	
Classification	ISO 12224 – 1.1.2.	ISO 12224 – 1.1.2.	
	Din 8511 – F – SW26	Din 8511 – F – SW26	
Electrical Reliability Test	Requirements	Results	
IPC SIR Testing (J-STD-004A)	1.0 × 10 <sup>8</sup> Ω minimum	PASS	

# **RECYCLING SERVICES**

We provide safe and efficient recycling services to help companies meet their environmental and legislative requirements and at the same time, maximize the value of their waste streams.

Our service collects solder dross, solder scrap, and various forms of solder paste waste. Please contact your local sales representative for recycling capabilities in your area or <u>link here</u>.









#### **SAFETY & WARNING**

It is recommended that the company/operator read and review the Safety Data Sheets for the appropriate health and safety warnings before use. **Safety Data Sheets are available at MacdermidAlpha.com/assembly-solutions/knowledge-base.** 

### STORAGE

ALPHA Cored Solder Wires should be stored in dry conditions and within a temperature range of 0 to 40 °C. Alpha guarantees the product shelf life for three years from the date of manufacture when stored in the recommended conditions.

## **CONTACT INFORMATION**

#### To confirm this document is the most recent version, please contact Assembly@MacDermidAlpha.com

www.macdermidalpha.com

North America 109 Corporate Blvd.	<b>Europe</b> Unit 2. Genesis Business Park	Asia 8/F., Paul Y. Centre
South Plainfield, NJ 07080, USA	Albert Drive	51 Hung To Road
1.800.367.5460	Woking, Surrey, GU21 5RW, UK 44.01483.758400	Kwun Tong, Kowloon, Hong Kong 852.3190.3100

Also read carefully warning and safety information on the Safety Data Sheet. This data sheet contains technical information required for safe and economical operation of this product. READ IT THOROUGHLY PRIOR TO PRODUCT USE . Emergency safety directory assistance: US 1 202 464 2554, Europe + 44 1235 239 670, Asia + 65 3158 1074, Brazil 0800 707 7022 and 0800 172 2020, Mexico 01800 002 1400 and (55) 5559 1588

DISCLAIMER: All statements, technical information and recommendations contained herein are based on tests we believe to be reliable, but the accuracy or completeness thereof is not guaranteed. No statement or recommendation shall constitute a representation unless set forth in an agreement signed by officers of seller and manufacturer. NO WARRANTY OF MERCHANTABILITY, WARRANTY OF FITNESS FOR A PARTICULAR PURPOSE OR ANY IMPLIED WARRANTY IN Following warranty is made in lieu of such warranties and all other warranties, express, implied, or statutory. Products are warranted to be free from defects in material and workmanship at the time sold. The sole obligation of seller and manufacturer under this warranty shall be to replace any noncompilant product at the time sold. Under no circumstances shall manufacturer or seller biable for any loss, damage or expense, direct, indirect, incidental or consequential, arising out of the inability to use the product. Notwithstanting the foregoing, if products are supplied in response to a custent that specifies operating parameters beyond those stated above, or if products are used under conditions exceeding said parameters, the customer by acceptance or use thereof assumes all risk of product failure and of all direct, indirect, incidental and consequential admages that may result from use of the products under such conditions, and agrees to exonerate, indemnify, defend and hold harmless MacDermid, Incorporated and its affiliates thereform. No suggestion for product use nor anything contained herein shall be construed as a recommendation to use any product in a manufacturer assume no responsibility or liability for any such infringement.

© 2019 MacDermid, Inc. and its group of companies. All rights reserved. "(R)" and "TM" are registered trademarks or trademarks of MacDermid, Inc. and its group of companies in the United States and/or other countries.

