

Data sheet | Item number: 855-4005/200-101

Split-core current transformer; Primary rated current: 200 A; Secondary rated current: 5 A; Rated power: 1 VA; Accuracy class: 1



www.wago.com/855-4005/200-101



 Picture differs from the item.

RoHS
Compliant





Item description

Short description:

WAGO's compact split-core current transformers are ideal for retrofitting existing systems. They are perfect for applications in which the current path must not be disrupted.

The transformer's accuracy permits extremely precise current measurements. The split-core current transformers are capable of supplying the specified rated power at

Subject to changes. Please also observe the further product documentation!

WAGO Kontakttechnik GmbH & Co. KG
Hansastr. 27
32423 Minden
Phone: +49571 887-0 | Fax: +49571 887-169
Email: info.de@wago.com | Web: www.wago.com

Do you have any questions about our products?
We are always happy to take your call at +49 (571) 887-44222.



the end of the secondary cable. All transformers are supplied with color-coded cables. Two UV-resistant cable ties are also included for secure and easy mounting.

Features:

- Current ratios from 200 A (primary side) and 5 A (secondary side)
- No measuring cable interruption
- Ideal for use in very confined spaces
- Rapid mounting
- For use around insulated cables up to 18 mm diameter
- Compact and hinged
- Color-coded connecting cable 0.5 m

Data**Technical data****Input – current transformer**

| | |
|--|-------------------------------|
| Primary rated current | 200 A |
| Rated continuous thermal current I_{cth} | 100 % |
| Rated short-time thermal current I_{th} | $60 \times I_N / 1 \text{ s}$ |
| Rated surge current I_{dyn} | $2.5 \times I_{th}$ |
| Rated frequency | 50 ... 60 Hz |

Output – current transformer

| | |
|-------------------------|------|
| Secondary rated current | 5 A |
| Rated power S_r | 1 VA |

Measurement error

| | |
|----------------|---|
| Accuracy class | 1 |
|----------------|---|

Safety and protection

| | |
|-------------------------------------|-------------------------|
| Highest voltage for equipment U_m | AC 720 V _{rms} |
| Protection type | IP20 |

Test voltage

| | |
|--------------|-----------------------|
| Test voltage | AC 3 kV; 50 Hz; 1 min |
|--------------|-----------------------|

Subject to changes. Please also observe the further product documentation!



Connection data

| | |
|---------------------------------------|---|
| Feedthrough for measurement conductor | Ø 18 mm |
| Cable type | 2 x 1.5 mm ² ; fine-stranded |
| Color code | black = S1; red = S2 |

Physical data

| | |
|--------------|-------|
| Cable length | 0.5 m |
|--------------|-------|

Mechanical data

| | |
|---------------|--|
| Mounting type | Split-core current transformer (suspended) |
|---------------|--|

Material data

| | |
|-----------------------------|-------|
| Insulation class | E |
| Flammability class per UL94 | V2 |
| Housing material | PA 66 |
| Weight | 400 g |

Environmental requirements

| | |
|---|-----------------------------------|
| Surrounding air temperature (operation) | -10 ... 55 °C |
| Surrounding air temperature (storage) | -20 ... 70 °C |
| Relative humidity | 5 ... 85 % (without condensation) |
| Operating altitude (max.) | 2000 m |

Standards and specifications

| | |
|--------------------------|------------------------|
| Conformity marking | CE |
| Standards/Specifications | EN 61869-1; EN 61869-2 |

Commercial data

| | |
|-----------------------|---------------|
| Packaging type | BOX |
| Country of origin | NL |
| GTIN | 4055143950596 |
| Customs tariff number | 85043180888 |

Subject to changes. Please also observe the further product documentation!

Compatible products

General accessories



Item no.: 857-551

Current signal conditioner; Current input signal; Current and voltage output signal; Digital output;
Configuration via software; Supply voltage: 24 VDC; 6 mm module width

www.wago.com/857-551

Downloads

Documentation

Bid Text

| | | |
|--------------|-----------------|----------|
| docx - Datei | docx 15.6 kB | Download |
| X81 - Datei | xml 5.5 kB | Download |

Instruction Leaflet

| | | | |
|-------------------------|------------------------|-----------------|----------|
| Kabelumbau-Stromwandler | V 1.1.0 15. 1. 2020 | pdf 832.5 kB | Download |
|-------------------------|------------------------|-----------------|----------|

Engineering-Software

Software for Interface-Products

| | | | |
|---|-------------------------|-----------------|----------|
| WAGO Interface Configuration Software G2 SMALL The full setup only includes the WAGO Interface Configuration Software G2. | 1.0.5.03 14. 9. 2020 | exe 29.8 MB | Download |
| WAGO Interface Configuration Software G2 FULL The full setup, in addition to the WAGO Interface Configuration Software G2, includes the installation for the Microsoft .NET Framework. | 1.0.5.03 14. 9. 2020 | exe 113.7 MB | Download |

Environmental Product Compliance

Compliance Search

| | | |
|---|-----|----------|
| Environmental Product Compliance 855-4005/200-101 Split-core current transformer; Primary rated current: 200 A; Secondary rated current: 5 A; Rated power: 1 VA; Accuracy class: 1 | URL | Download |
|---|-----|----------|

Installation Notes

Subject to changes. Please also observe the further product documentation!

WAGO Kontakttechnik GmbH & Co. KG
Hansastr. 27
32423 Minden
Phone: +49571 887-0 | Fax: +49571 887-169
Email: info.de@wago.com | Web: www.wago.com

Do you have any questions about our products?
We are always happy to take your call at +49 (571) 887-44222.

Installation



Simple termination!



Quick and easy mounting!



Subject to changes. Please also observe the further product documentation!

WAGO Kontakttechnik GmbH & Co. KG
Hansastr. 27
32423 Minden
Phone: +49571 887-0 | Fax: +49571 887-169
Email: info.de@wago.com | Web: www.wago.com

Do you have any questions about our products?
We are always happy to take your call at +49 (571) 887-44222.