



Product information



Active Tip Heating Techology Micro soldering iron WXMP 55 W, 12 V

- For WX stations
- Fine slim soldering iron. Ideal for microscope work.
- High performance by integrated active soldering tip.

Please not that the soldering tip is not included!

Technical data	
Voltage (heater):	12 V
Heating output:	40 W (55W with RT 11)
Heat-up time:	approx. 3 s 50°C - 350°C (120°F - 660°F)
Temperature range:	100°C - 450°C (212°F - 850°F)
Tip type:	RT
Connectable to:	Weller WX Stations

Note: The WXMP soldering iron by Weller may only be used with Weller WX supply units.

Active Tip Heating Technology

- Quick tip exchange without any tools
- Extremely short heating time 100°/sec.
- Energy saving by standby function
- Optimal reaction time

Optimum for soldering applications

Optimal tool where heating element and sensor are integrated in the soldering tip. By lowering the soldering joint temperature a faster reaction time is possible. With this tool the performance is exactly at the solder



joint.