## Manual 0-10v Controller



The RM-ECi controller is for use with the full range of ebm-papst EC fans. Powered by the 10VDC output from the motor, it provides infinitely variable, manual speed control between 0% and 100%.

|                  | Supply Voltage | Maximum<br>Ambient Temperature | IP Rating | Height | Width | Depth |
|------------------|----------------|--------------------------------|-----------|--------|-------|-------|
| Part Number      | VDC            | °C                             |           | mm     | mm    | mm    |
|                  |                |                                |           |        |       |       |
| RM-ECi           | 10             | 50                             | 54        | 65     | 65    | 80    |
| CN1003 (Unboxed) | 10             | 50                             | 00        | 36     | 36    | 50    |
|                  |                |                                |           |        |       |       |

- Can control multiple fans running at the same speed
- Stepless control knob for infinitely variable speed setting
- Cable entries 4 x M16 or M20
- 4mm mounting holes

