


Data sheet | Item number: 765-1703/200-000

16-channel digital input/output; IO Link Class A Hub; DC 24 V / 2.0 A; 8xM12 connection; HubLine



www.wago.com/765-1703/200-000



Data

Technical Data

IO-Link

Communication	IO-Link Class A Slave
Connection technology: communication/fieldbus	1 x A-coded M12; 5-pole

Gerätefunktionen

Parameter	Input filter Output current Temperature
Diagnostics	Undervoltage; Overcurrent; Overload; Overtemperature

Digitalein-/ausgänge

Number of digital inputs	16
Number of digital outputs	16
Connection technology: inputs/outputs	8 x A-coded M12; 5-pole

Subject to changes. Please also observe the further product documentation!

WAGO Kontakttechnik GmbH & Co. KG
Hansastr. 27
32423 Minden
Phone: +49571 887-0 | Fax: +49571 887-169
Email: info.de@wago.com | Web: www.wago.com

Do you have any questions about our products?
We are always happy to take your call at +49 (571) 887-44222.



Input characteristic	High-side switching
Input filter	0.2 ... 20 ms
Input characteristic	Type 3, per IEC 61131-2
Output current (per channel)	2 A

Versorgung

Connection technology: supply	1 x A-coded M12; 5-pole; via IO-Link port (1L)
Supply voltage	24 VDC (18 ... 31.2 V); 1L
Power consumption (max.)	4000 mA
Power consumption (note)	1L: 0.2 A + load current
Reverse voltage protection	Yes

Geometrical Data

Width	60 mm / 2.362 inch
Height	30 mm / 1.181 inch
Depth	158.5 mm / 6.24 inch

Mechanical Data

Weight	170 g
Conformity marking	CE

Environmental Requirements

Surrounding air temperature (operation)	-25 ... 70 °C
Surrounding air temperature (storage)	-40 ... 80 °C
Protection type	IP67
Protection class	III per EN 61140, IEC 61140, VDE 0140-1
Operating altitude	0 ... 2000 m 0 ... 2000 m
Pollution degree (5)	3 per EN 60664-1 3 (EN 60664-1)
Overvoltage category	II (EN 60664-1)
Vibration resistance	5g per IEC 60068-2-6
Shock resistance	Short-term: 50g/11 ms/half-sine per IEC 60068-2-27; Long-term: 30g/6 ms/half-sine per IEC 60068-2-29
EMC immunity to interference	per EN 61000-6-2
EMC emission of interference	per EN 61000-6-4

Subject to changes. Please also observe the further product documentation!

WAGO Kontakttechnik GmbH & Co. KG
 Hansastr. 27
 32423 Minden
 Phone: +49571 887-0 | Fax: +49571 887-169
 Email: info.de@wago.com | Web: www.wago.com

Do you have any questions about our products?
 We are always happy to take your call at +49 (571) 887-44222.

Commercial data

Packaging type	BOX
Country of origin	DE
GTIN	4055143949989
Customs tariff number	85371098990

Required accessories

tools


	Item no.: 206-701 Torque wrench M8 and M12; Assembly kit	www.wago.com/206-701
--	--	--


protection

	Item no.: 756-8102 M12 protective cap; for unused sockets; -	www.wago.com/756-8102
--	--	--

	Item no.: 756-8103 M12 protective cap; for unused plugs; -	www.wago.com/756-8103
--	--	--

Marking accessories


	Item no.: 2009-110 Marking strips; for Smart Printer; on reel; not stretchable; plain; snap-on type; white	www.wago.com/2009-110
--	--	--

	Item no.: 2009-115 WMB-Inline; for Smart Printer; 1500 pieces on roll; stretchable 5 - 5.2 mm; plain; snap-on type; white	www.wago.com/2009-115
---	---	--

Compatible products

wiring and connectors

	Item no.: 756-5301/050-015 Sensor/Actuator cable; 5-pole; Length: 1.5 m	www.wago.com/756-5301/050-015
--	---	--

	Item no.: 756-5301/050-050 Sensor/Actuator cable; 5-pole; Length: 5 m	www.wago.com/756-5301/050-050
--	---	--

	Item no.: 756-5301/050-100 Sensor/Actuator cable; 5-pole; Length: 10 m	www.wago.com/756-5301/050-100
--	--	--

	Item no.: 756-5302/050-015 Sensor/Actuator cable; 5-pole; Length: 1.5 m	www.wago.com/756-5302/050-015
--	---	--

	Item no.: 756-5302/050-050 Sensor/Actuator cable; 5-pole; Length: 5 m	www.wago.com/756-5302/050-050
--	---	--

Subject to changes. Please also observe the further product documentation!



Item no.: 756-5302/050-100
Sensor/Actuator cable; 5-pole; Length: 10 m

www.wago.com/756-5302/050-100



Item no.: 756-5311/040-015
Sensor/Actuator cable; 4-pole; Length: 1.5 m

www.wago.com/756-5311/040-015



Item no.: 756-5311/040-050
Sensor/Actuator cable; 4-pole; Length: 5 m

www.wago.com/756-5311/040-050



Item no.: 756-5311/040-100
Sensor/Actuator cable; 4-pole; Length: 10 m

www.wago.com/756-5311/040-100



Item no.: 756-5312/040-015
Sensor/Actuator cable; 4-pole; Length: 1.5 m

www.wago.com/756-5312/040-015



Item no.: 756-5312/040-050
Sensor/Actuator cable; 4-pole; Length: 5 m

www.wago.com/756-5312/040-050



Item no.: 756-5312/040-100
Sensor/Actuator cable; 4-pole; Length: 10 m

www.wago.com/756-5312/040-100



Item no.: 756-5401/040-010
Sensor/Actuator cable; 4-pole; Length: 1 m

www.wago.com/756-5401/040-010



Item no.: 756-5401/040-020
Sensor/Actuator cable; 4-pole; Length: 2 m

www.wago.com/756-5401/040-020



Item no.: 756-5401/050-010
Sensor/Actuator cable; 5-pole; Length: 1 m

www.wago.com/756-5401/050-010



Item no.: 756-5401/050-020
Sensor/Actuator cable; 5-pole; Length: 2 m

www.wago.com/756-5401/050-020



Item no.: 756-5402/040-010
Sensor/Actuator cable; 4-pole; Length: 1 m

www.wago.com/756-5402/040-010



Item no.: 756-5402/040-020
Sensor/Actuator cable; 4-pole; Length: 2 m

www.wago.com/756-5402/040-020

Subject to changes. Please also observe the further product documentation!



Item no.: 756-5402/050-010
Sensor/Actuator cable; 5-pole; Length: 1 m

www.wago.com/756-5402/050-010



Item no.: 756-5402/050-020
Sensor/Actuator cable; 5-pole; Length: 2 m

www.wago.com/756-5402/050-020



Item no.: 756-5403/040-010
Sensor/Actuator cable; 4-pole; Length: 1 m

www.wago.com/756-5403/040-010



Item no.: 756-5403/040-020
Sensor/Actuator cable; 4-pole; Length: 2 m

www.wago.com/756-5403/040-020



Item no.: 756-5403/050-010
Sensor/Actuator cable; 5-pole; Length: 1 m

www.wago.com/756-5403/050-010



Item no.: 756-5403/050-020
Sensor/Actuator cable; 5-pole; Length: 2 m

www.wago.com/756-5403/050-020



Item no.: 756-5404/040-010
Sensor/Actuator cable; 4-pole; Length: 1 m

www.wago.com/756-5404/040-010



Item no.: 756-5404/040-020
Sensor/Actuator cable; 4-pole; Length: 2 m

www.wago.com/756-5404/040-020



Item no.: 756-5404/050-010
Sensor/Actuator cable; 5-pole; Length: 1 m

www.wago.com/756-5404/050-010



Item no.: 756-5404/050-020
Sensor/Actuator cable; 5-pole; Length: 2 m

www.wago.com/756-5404/050-020



Item no.: 756-5507/040-010
Sensor/Actuator cable; 4-pole; Length: 1 m

www.wago.com/756-5507/040-010



Item no.: 756-5507/040-020
Sensor/Actuator cable; 4-pole; Length: 2 m














www.wago.com/756-5507/040-020



Item no.: 756-5508/040-010
Sensor/Actuator cable; 4-pole; Length: 1 m

www.wago.com/756-5508/040-010

Subject to changes. Please also observe the further product documentation!

	Item no.: 756-5508/040-020 Sensor/Actuator cable; 4-pole; Length: 2 m	www.wago.com/756-5508/040-020
	Item no.: 756-5509/040-010 Sensor/Actuator cable; 4-pole; Length: 1 m	www.wago.com/756-5509/040-010
	Item no.: 756-5509/040-020 Sensor/Actuator cable; 4-pole; Length: 2 m	www.wago.com/756-5509/040-020
	Item no.: 756-5510/040-010 Sensor/Actuator cable; 4-pole; Length: 1 m	www.wago.com/756-5510/040-010
	Item no.: 756-5510/040-020 Sensor/Actuator cable; 4-pole; Length: 2 m	www.wago.com/756-5510/040-020
	Item no.: 756-5513/040-010 Sensor/Actuator cable; 4-pole; Length: 1 m	www.wago.com/756-5513/040-010
	Item no.: 756-5513/040-020 Sensor/Actuator cable; 4-pole; Length: 2 m	www.wago.com/756-5513/040-020
	Item no.: 756-5514/040-010 Sensor/Actuator cable; 4-pole; Length: 1 m	www.wago.com/756-5514/040-010
	Item no.: 756-5514/040-020 Sensor/Actuator cable; 4-pole; Length: 2 m	www.wago.com/756-5514/040-020
	Item no.: 756-9202/050-000 Accessories; 5-pole	www.wago.com/756-9202/050-000
	Item no.: 756-9205/050-000 Accessories; 5-pole	www.wago.com/756-9205/050-000
	Item no.: 756-9212/050-000 Accessories; 5-pole	www.wago.com/756-9212/050-000
	Item no.: 756-9215/050-000 Accessories; 5-pole	www.wago.com/756-9215/050-000

Subject to changes. Please also observe the further product documentation!



Item no.: 756-9301/040-000
Accessories; 4-pole

www.wago.com/756-9301/040-000



Item no.: 756-9301/050-000
Accessories; 5-pole

www.wago.com/756-9301/050-000

Downloads

Documentation

Manual

16-Channel Digital Input/Output; IO-Link Class A Hub DC 24 V / 2.0 A; 8xM12 Connection; HubLine	V 1.1.0 30. 11. 2020	pdf 2.9 MB	Download
--	-------------------------	---------------	----------

System Description

WAGO I/O System Field; General Product Information		pdf 708.2 kB	Download
--	--	-----------------	----------

Engineering-Software

WAGO IO-Link Configurator

WAGO IO-Link Configurator	V5.1.1 17. 12. 2020	ZIP 25.2 MB	Download
---------------------------	------------------------	----------------	----------

The WAGO IO-Link Configurator is standalone commissioning, configuration and management software for the WAGO Field I/O System's IO-Link Master and Hubs.

It supports all IO-Link devices per the IO-Link specification and allows automatic download of IO-DDs via integrated IO-DD Finder.

Register now and test our engineering software for 30 days at no cost.

Runtime Software

Firmware

IO-Field 765-17xx Firmware Download	01	zip 340.6 kB	Download
-------------------------------------	----	-----------------	----------

CAD/CAE-Data

CAD data

2D/3D Models 765-1703/200-000		URL	Download
-------------------------------	--	-----	----------

Subject to changes. Please also observe the further product documentation!



CAE data

ZUKEN Portal 765-1703/200-000

[URL](#)

[Download](#)

Environmental Product Compliance

Compliance Search

Environmental Product Compliance 765-1703/200-000

[URL](#)

[Download](#)

16-channel digital input/output; IO Link Class A Hub; DC 24 V / 2.0 A; 8xM12 connection; HubLine

Installation Notes

Product family

I/O System Field

[Show all products from the family](#)

Subject to changes. Please also observe the further product documentation!

WAGO Kontakttechnik GmbH & Co. KG

Hansastr. 27

32423 Minden

Phone: +49571 887-0 | Fax: +49571 887-169

Email: info.de@wago.com | Web: www.wago.com

Do you have any questions about our products?

We are always happy to take your call at +49 (571) 887-44222.