

(E 0102


Model Number

RJ15-14-N


Features

- Comfort series
- 15 mm inside diameter

Connection



Dimensions



-		
Technical Data		
General specifications		
Switching element function		NAMUR NC
Inside diameter		15 mm
Installation		
Output polarity		NAMUR
Measuring cylinder		9S20K
Diameter		3 mm
Length		6 mm
Nominal ratings		
Nominal voltage	U_o	8 V
Operating voltage	U_B	5 25 V
Switching frequency	f	0 1500 Hz
Current consumption		
Measuring plate not detected		≥ 3 mA
Measuring plate detected		≤ 1 mA
Ambient conditions		
Ambient temperature		-25 70 °C (248 343 K)
Mechanical specifications		
Connection type		2 m, PVC cable
Core cross-section		0.14 mm ²
Housing material		PBT
Protection degree		IP67
General information		
Use in the hazardous area		see instruction manuals
Category		2G
Compliance with standards and ves	directi-	
Standard conformity		
NAMUR		EN 60947-5-6:2000
Standards		EN 60947-5-2:2007 IEC 60947-5-2:2007

ATEX 2G

Instruction

Device category 2G

Directive conformity Standard conformity

CE symbol

Ex-identification

EC-Type Examination Certificate

Appropriate type

Effective internal capacitance Ci

Effective internal inductance Li

General

Highest permissible ambient temperature

Installation, Comissioning

Maintenance

[Fett]Special conditions

Manual electrical apparatus for hazardous areas

for use in hazardous areas with gas, vapour and mist

EN 60079-0:2006, EN 60079-11:2007 Ignition protection "Intrinsic safety" Use is restricted to the following stated conditions €0102

⟨Ex⟩ II 2G Ex ia IIC T6

PTB 99 ATEX 2128 X

RJ15-...-N...

≤ 130 nF; a cable length of 10 m is considered.

 \leq 20 μH ; a cable length of 10 m is considered.

The apparatus has to be operated according to the appropriate data in the data sheet and in this instruction manual. The EC-Type Examination Certificate has to be observed. The special conditions must be adhered to!

The temperature ranges, according to temperature class, are given in the EC-Type Examination Certificate.

Laws and/or regulations and standards governing the use or intended usage goal must be observed. The intrinsic safety is only assured in connection with an appropriate related apparatus and according to the proof of intrinsic safety.

No changes can be made to apparatus, which are operated in hazardous areas. Repairs to these apparatus are not possible.

PEPPERL+FUCHS